

Мануал по настройке роутера D-Link DIR-615.



Авторизация.

Для того, что бы попасть в веб-интерфейс роутера, необходимо открыть ваш Интернет браузер и в строке адреса набрать `http://192.168.0.1` , User Name `admin` , Password – оставить пустым (при условии, что роутер имеет заводские настройки, и его IP не менялся).

Product Page: DIR-615 Hardware Version: E4 Firmware Version: 5.10RU

LOGIN

Log in to the router:

User Name : Admin

Password :

Login

WIRELESS

Copyright © 2004-2010 DLink, Inc.

Настройка Wi-Fi на роутере.

В интерфейсе роутера необходимо выбирать вкладку «*SETUP*», слева — «*Wireless Settings*». Здесь нажимаем кнопку «*Manual Wireless Connection Setup*».

Product Page: DIR-615 Hardware Version: E4 Firmware Version: 5.10RU

WIRELESS SETTINGS

The following Web-based wizards are designed to assist you in your wireless network setup and wireless device connection.

Before launching these wizards, please make sure you have followed all steps outlined in the Quick Installation Guide included in the package.

WIRELESS NETWORK SETUP WIZARD

This wizard is designed to assist you in your wireless network setup. It will guide you through step-by-step instructions on how to set up your wireless network and how to make it secure.

[Wireless Network Setup Wizard](#)

Note: Some changes made using this Setup Wizard may require you to change some settings on your wireless client adapters so they can still connect to the D-Link Router.

ADD WIRELESS DEVICE WITH WPS (WI-FI PROTECTED SETUP) WIZARD

This wizard is designed to assist you in connecting your wireless device to your router. It will guide you through step-by-step instructions on how to get your wireless device connected. Click the button below to begin.

[Add Wireless Device with WPS](#)

MANUAL WIRELESS NETWORK SETUP

If your wireless network is already set up with Wi-Fi Protected Setup, manual configuration of the wireless network will destroy the existing wireless network. If you would like to configure the wireless settings of your new D-Link Systems Router manually, then click on the Manual Wireless Network Setup button below.

[Manual Wireless Network Setup](#)

Helpful Hints...

If you are new to wireless networking and have never configured a wireless router before, click on **Wireless Network Setup Wizard** and the router will guide you through a few simple steps to get your wireless network up and running.

If you consider yourself an advanced user and have configured a wireless router before, click **Manual Wireless Network Setup** to input all the settings manually.

[More...](#)

Далее

Выставляем параметры:

1. В разделе «WI-FI PROTECTED SETUP» с пункта Enable галочку лучше снять, поскольку не все беспроводные адаптеры поддерживают технологию Wi-Fi Protected Setup.»
2. Ставим галочку «Enable Wireless»; «Always»
3. В графе «Wireless Network Name» пишем название для беспроводной сети.
4. 802.11 Mode – Mixed 802.11n, 802.11n and 802.11b.
5. Security Mode: WPA-Personal;
6. WPA Mode: WPA-Only;
7. Cipher Type: AES;
8. Pre-Shared Key: сюда вводим пароль для доступа в беспроводную сеть. В качестве пароля используйте Серийный номер, указанный на коробке (S/N) . После того, как все параметры введены, нажимаем кнопку «Save Settings». На этом настройка Wi-Fi на маршрутизаторе D-Link DIR-615 закончена.

DIR-615	SETUP	ADVANCED	TOOLS	STATUS	SUPPORT
INTERNET	WIRELESS				<p>Helpful Hints...</p> <p>Changing your Wireless Network Name is the first step in securing your wireless network. Change it to a familiar name that does not contain any personal information.</p> <p>Enable Auto Channel Scan so that the router can select the best possible channel for your wireless network to operate on.</p> <p>Enabling Hidden Mode is another way to secure your network. With this option enabled, no wireless clients will be able to see your wireless network when they scan to see what's available. For your wireless devices to connect to your router, you will need to manually enter the Wireless Network Name on each device.</p> <p>If you have enabled Wireless Security, make sure you write down the Key or Passphrase that you have configured. You will need to enter this information on any wireless device that you connect to your wireless network.</p> <p>More...</p>
WIRELESS SETTINGS	<p>Use this section to configure the wireless settings for your D-Link Router. Please note that changes made on this section may also need to be duplicated on your Wireless Client.</p> <p>Save Settings Don't Save Settings</p>				
NETWORK SETTINGS	<p>WI-FI PROTECTED SETUP (ALSO CALLED WCN 2.0 IN WINDOW VISTA) :</p> <p>Enable : <input checked="" type="checkbox"/></p> <p>Current PIN : 23318485</p> <p>Generate New PIN Reset PIN to Default</p> <p>Wi-Fi Protected Status : Enabled/Not Configured</p> <p>Reset to Unconfigured</p>				
	<p>WIRELESS NETWORK SETTINGS</p> <p>Enable Wireless : <input checked="" type="checkbox"/> Always Add New</p> <p>Wireless Network Name : dlink (Also called the SSID)</p> <p>802.11 Mode : Mixed 802.11n, 802.11g and 802.11b</p> <p>Enable Auto Channel Scan : <input checked="" type="checkbox"/></p> <p>Wireless Channel : 2.437 GHz - CH 6</p> <p>Channel Width : Auto 20/40 MHz</p> <p>Visibility Status : <input checked="" type="radio"/> Visible <input type="radio"/> Invisible</p>				
	<p>WIRELESS SECURITY MODE</p> <p>To protect your privacy you can configure wireless security features. This device supports three wireless security modes including: WEP, WPA-Personal, and WPA-Enterprise. WEP is the original wireless encryption standard. WPA provides a higher level of security. WPA-Personal does not require an authentication server. The WPA-Enterprise option requires an external RADIUS server.</p> <p>Security Mode : WPA-Personal</p>				
	<p>WPA</p> <p>Use WPA or WPA2 mode to achieve a balance of strong security and best compatibility. This mode uses WPA for legacy clients while maintaining higher security with stations that are WPA2 capable. Also the strongest cipher that the client supports will be used. For best security, use WPA2 Only mode. This mode uses AES(CCMP) cipher and legacy stations are not allowed access with WPA security. For maximum compatibility, use WPA Only. This mode uses TKIP cipher. Some gaming and legacy devices work only in this mode.</p> <p>To achieve better wireless performance use WPA2 Only security mode (or in other words AES cipher).</p> <p>WPA Mode : WPA Only</p> <p>Cipher Type : AES</p> <p>Group Key Update Interval : 3600 (seconds)</p>				
	<p>PRE-SHARED KEY</p> <p>Enter an 8- to 63-character alphanumeric pass-phrase. For good security it should be of ample length and should not be a commonly known phrase.</p> <p>Pre-Shared Key : Укажите S/N с коробки</p>				

Настройка подключения к Интернет в режиме роутера.

Нажимаем кнопку Manual Internet Connection Setup



DIR-615 //	SETUP	ADVANCED	TOOLS	STATUS	SUPPORT
INTERNET	<p>INTERNET CONNECTION</p> <p>There are two ways to set up your Internet connection: you can use the Web-based Internet Connection Setup Wizard, or you can manually configure the connection.</p> <p>INTERNET CONNECTION SETUP WIZARD</p> <p>If you would like to utilize our easy to use Web-based Wizards to assist you in connecting your new D-Link Systems Router to the Internet, click on the button below.</p> <p style="text-align: center;"><input type="button" value="Internet Connection Setup Wizard"/></p> <p>Note: Before launching these wizards, please make sure you have followed all steps outlined in the Quick Installation Guide included in the package.</p> <p>MANUAL INTERNET CONNECTION OPTIONS</p> <p>If you would like to configure the Internet settings of your new D-Link Systems Router manually, then click on the button below.</p> <p style="text-align: center;"><input type="button" value="Manual Internet Connection Setup"/> ←</p>				<p>Helpful Hints...</p> <p>If you are new to networking and have never configured a router before, click on Internet Connection Setup Wizard and the router will guide you through a few simple steps to get your network up and running.</p> <p>If you consider yourself an advanced user and have configured a router before, click Manual Internet Connection Setup to input all the settings manually.</p> <p>More...</p>
WIRELESS SETTINGS					
NETWORK SETTINGS					
WIRELESS					

Настройка в режиме роутера.

1. Настройка PPPoE при автоматическом получении локального IP адреса (DHCP).
2. My Internet Connection is: Russian PPPoE (Dual Access)
3. User Name: Ваш логин из договора
4. Password: Ваш пароль из договора
5. Verify Password: повтор пароля
6. Нажимаем кнопку Clone MAC Address
7. Connect mode select – режим установки соединения «Always on» для постоянного подключения (рекомендуется).
8. MTU – 1472.
9. Сохраняем настройки кнопкой Save Settings и ждем пока роутер перезагрузится.

DIR-615	SETUP	ADVANCED	TOOLS	STATUS	SUPPORT
INTERNET	WAN				Helpful Hints...
WIRELESS SETTINGS	Use this section to configure your Internet Connection type. There are several connection types to choose from: Static IP, DHCP, PPPoE, PPTP and L2TP. If you are unsure of your connection method, please contact your Internet Service Provider.				When configuring the router to access the Internet, be sure to choose the correct
NETWORK SETTINGS	Note: If using the PPPoE option, you will need to remove or disable any PPPoE client software on your computers.				Internet Connection Type from the drop down menu. If you are unsure of which option to choose, contact your
<input type="button" value="Save Settings"/> <input type="button" value="Don't Save Settings"/>					Internet Service Provider (ISP) .
INTERNET CONNECTION TYPE					If you are having trouble accessing the Internet through the router, double check any settings you have entered on this page and verify them with your ISP if needed.
Choose the mode to be used by the router to connect to the Internet.					More...
My Internet Connection is : <input type="text" value="Russia PPPoE (Dual Access)"/>					
RUSSIA PPPOE (DUAL ACCESS) :					
Enter the information provided by your Internet Service Provider (ISP).					
Address Mode : <input checked="" type="radio"/> Dynamic IP <input type="radio"/> Static IP					
IP Address : <input type="text" value="0.0.0.0"/>					
User Name : <input type="text" value="Логин на Интернет"/>					
Password : <input type="text" value="Пароль на Интернет"/>					
Verify Password : <input type="text" value="Пароль на Интернет"/>					
Service Name : <input type="text"/> (optional)					
Reconnect Mode : <input checked="" type="radio"/> Always on <input type="radio"/> On demand <input type="radio"/> Manual					
Maximum Idle Time : <input type="text" value="5"/> (minutes, 0=infinite)					
MTU : <input type="text" value="1472"/> (bytes)MTU default = 1492					
MAC Address : <input type="text" value="48:5B:39:5F:0E:0A"/>					
<input type="button" value="Clone Your PC's MAC Address"/>					